



Electrocomponentes S.A.
www.electrocomponentes.com



PD-20 and PD-28 are high voltage probes. They measure both AC and DC voltages with your multimeter. They consist of 2 kinds of contact tips, a test clip for the ground , a set of test leads for multimeter and a high quality enclosure. The enclosure has very good insulation properties.

They are light-weight and rugged.

2 kinds of contact tips are available.

One is a round needle tip for normal use.

Another is a special flat spring type for CRT anode.

Before taking any measurements, first connect the alligator clip of this probe to earth ground and make sure connection is proper.

SPECIFICATIONS

PD-20

Input Impedance	500 M Ω
Attenuation Ratio	1000 : 1
Accuracy	DCV (0 ~ 20kV) \pm 1%, DCV (20kV ~ 30kV) \pm 2% ACV (0 ~ 20kV) typically \pm 5% at 60 Hz
Max. Working Voltage	30kV DC or 20kV AC
Operating Temperature	0°C ~ 50°C
Storage Temperature	-10°C ~ 60°C
Cable Length	1 m
Weight	Approx. 260g
Note	PD-20 is a high voltage probe that is used with DMM



Electrocomponentes S.A.
www.electrocomponentes.com